


740 PARAGON RESIDENTIAL SERIES

SPECIFICATIONS

FIXTURE	SOCKET TYPE	OPTICAL SYSTEMS	BB BALLAST BOX	POST FITTER
---------	-------------	-----------------	----------------	-------------

←7 1/2"→



14 3/4"


740



MED
Single
Medium
Base Socket



PL
Compact
Fluorescent



HSS
House
Side
Shield



FMC
Frosted
Mission
Chimney

78BB - Large Scale
for up to 100 watt
ballasts



27BB - Hanging or
Pier for up to 100
watt ballasts




○ R3"

□ S4"


○ R4"

SIZES

LENSES



CA
Clear
Acrylic



CSA
Clear
Seeded
Acrylic



CTA
Clear
Textured
Acrylic



PA
Prismatic
Acrylic




WA
White
Acrylic



AGB
Art Glass
Brown
Marble

POST MOUNT, WALL BRACKETS & PIER MOUNT


←7 1/2"→



14 3/4"

740WB


←14 1/2"→
←7 1/2"→



14 3/4"

740/77WB

←14 1/2"→
←7 1/2"→



15 1/2"

740/HMA3


←7 1/2"→



36"

740HCH27††


←7 1/2"→



36"

740HSH27††


←15 1/2"→
←7 1/2"→



21 1/4"

740/TPS3


←7 1/2"→



18"

740 PB

←7 1/2"→



17 3/4"

740 PT†

NOTE: 740 Series 100W Max. INC. Refractors not available.
† Remote Ballast required if HID or CF. †† Add BB Ballast Box for 100W HID.


BUILDING A PART NUMBER

POST & ARM FIXTURES



ARM MOUNTED FIXTURE NO. OF ARMS	CENTER POST TOP FIXTURE (PT) FIXT./FITTER	POST (See Post Section)	POST CAP	LIGHT SOURCE BALLAST WATTS / TYPE / VOLTS	OPTICS	OPTIONS	LENS	FINISH
740	S4	4SQX		100 MHP120			WA	BKT

WALL FIXTURES



FIXTURE / WALL BRACKET	LIGHT SOURCE BALLAST WATTS / TYPE / VOLTS	OPTICS	OPTIONS	LENS	FINISH
740/TPS3	100 MHP120		MHP100/MED	WA	BKT



PIER FIXTURES
Uses same information
boxes as wall fixture
740/P28B
FIXTURE / PIER BASE

HANGING FIXTURES



FIXTURE / HANGING BRACKET	OVERALL DROP IN INCHES	LIGHT SOURCE BALLAST WATTS / TYPE / VOLTS	OPTICS	OPTIONS	LENS	FINISH
740H/CH27	36 INCHES	100 MHP120	FMC	MHP100/MED	CA	BKT

PART NUMBER SELECTIONS

FIXTURES <ul style="list-style-type: none"> • 740 	POST ARMS <ul style="list-style-type: none"> • 77PM • HMA3PM • TPS3PM 	WALL BRACKET ARMS <ul style="list-style-type: none"> • 77WB • HMA3WB • TPS3WB 	LAMPS⁴ <ul style="list-style-type: none"> • HPS35/MED • HPS50/MED • HPS70/MED • HPS100/MED • MHP50/MED • MHP70/MED • MHP100/MED • PLT26 • PLT32 • PLT42 • PLT57 • PLT70 	BALLASTS^{3,4} <ul style="list-style-type: none"> • 35HPS¹ • 50HPS • 70HPS • 100HPS • 50MHP • 70MHP • 100MHP • 26PLT • 32PLT • 42PLT • 57PLT • INCAND (100 watt max.) 	BB-BALLAST BOX <ul style="list-style-type: none"> • 78BB - Medium Scale for up to 100 watt ballasts • 27BB - Hanging or Pier for up to 100 watt ballasts 	STANDARD FINISHES* <ul style="list-style-type: none"> • BKT Black Textured • WHT White Textured • PGT Park Green Textured • ABZT Architectural Medium Bronze Textured • DBT Dark Bronze Textured <p><small>*Smooth Finishes are available upon request</small></p>
OPTICS <ul style="list-style-type: none"> • HSS • FMC • MED • PL 	LENSES <ul style="list-style-type: none"> • CA • CSA • CTA • PA • WA • AGB 	HANGING BRACKETS <ul style="list-style-type: none"> • CH27 • SH27 				CUSTOM FINISHES <ul style="list-style-type: none"> • OI Old Iron • RT Rust • WBR Weathered Brown • CD Cedar • WBK Weathered Black • TT Two Tone
FITTERS <ul style="list-style-type: none"> • R3 • S4 • R4 		PIER BASE <ul style="list-style-type: none"> • P28B 				STERNBERG SELECT FINISHES <ul style="list-style-type: none"> • VG Verde Green • SI Swedish Iron • OWGT Old World Gray Textured

OPTIONS

- PEC1-E Photocell-Electronic 120-277 Volt
- FHS Single Fuse and Holder-120,277 Volt
- LAMPS Select from List

NOTES:

- ¹35HPS is 120 volt only.
- ²MED base only when used to house lamp.
- ³Medium base sockets standard with ballasts up to 100 watts for HID. 4-pin for PL.
- ⁴Metal halide systems are pulse start.